



FACTORY SEALED CONTROLS - INTRODUCTION

SEAL-XM®



Class I, Div. 1 & 2, Groups B, C, D
Class I, Zone 1 & 2, Groups IIB, IIA
Class II, Div. 1 & 2, Groups E, F, G
Class III
Type 3

 Certified File 2493125

FEATURES-SPECIFICATIONS

Features

- Incorporates Factory Sealed Universal contact blocks and GOB3 LED pilot light devices
- External sealing fitting not required on standard assemblies. Group B configurations require sealing fitting beyond 60".
- No seal plate between the electrical device and back box allows direct wiring to contact terminals
- Type 3 weatherproof
- Grounding boss supplied in the splice box
- Sold as complete units with 1/2", 3/4", or 1" hubs, in Dead End or Feed Thru configurations.
- More wiring room in back box

Materials

FXCS-*-M Groups C, D
Copper free aluminum cover & box
FXCS-*-MB Groups B, C, D
Copper free aluminum cover & box
FXCS-*-MBI Groups B, C, D
Copper free aluminum cover & ductile iron back box zinc electroplated
FXCS-*-MI Groups C, D
Copper free aluminum cover & ductile iron back box zinc electroplated
• Stainless steel captive cover screws
• Operating shafts stainless steel
• Standard finish is a grey epoxy powder baked on for ultimate corrosion resistance

Hazardous Rating:

Class I, Division 2, Groups A,B,C,D;
 Class I, Zone 1, Group IIC

Terminal Capacity:

22 thru 12 AWG [0.52-2.5mm²] copper, solid or stranded conductors. Tightening torque: 20 in-lbs (2.2Nm)

Contact Electrical Ratings:

NEMA A600/P600 - Pilot Duty; 690VAC, 10A, 50-60Hz; 1/2HP @ 120VAC; 1HP @ 208/240/277 VAC; 60VDC, 5A; 110VDC, 2A; 250VDC, 1.5A; 600VDC, 0.2A

Pilot Light Electrical Ratings:


250 VAC max.



CONTROLS

SEAL-XM™ SERIES

FACTORY SEALED CONTROLS - CATALOG LOGIC





FACTORY SEALED CONTROL STATIONS



Single Push Button



Double Push Button



LED Pilot Light

SEAL-XM MOMENTARY CONTACT SINGLE PUSH BUTTON

SEAL-XM MOMENTARY CONTACT SINGLE PUSH BUTTON					
CATALOG NUMBER		HUB SIZE	DIAGRAM	BUTTON COLOR	LEGEND PLATE MARKING
BOX COVER					
DEAD-END	FEED-THRU				
FXCS-1B1-M	FXCS-4B1-M	1/2"		Green	Start
FXCS-2B1-M	FXCS-5B1-M	3/4"			
FXCS-1B2-M	FXCS-4B2-M④	1/2"		Red	Stop
FXCS-2B2-M	FXCS-5B2-M④	3/4"			
FXCS-1B3-M	FXCS-4B3-M	1/2"		Black	Specify
FXCS-2B3-M	FXCS-5B3-M	3/4"			

SEAL-XM MOMENTARY CONTACT DOUBLE PUSH BUTTON

SEAL-XM MOMENTARY CONTACT DOUBLE PUSH BUTTON					
CATALOG NUMBER		HUB SIZE	DIAGRAM	BUTTON COLOR	LEGEND PLATE MARKING
BOX & COVER					
DEAD-END	FEED-THRU				
FXCS-1B4-M	FXCS-4B4-M	1/2"		Green/Red	Start/Stop
FXCS-2B4-M	FXCS-5B4-M	3/4"			
FXCS-1B5-M	FXCS-4B5-M	1/2"		Green/Green	Specify
FXCS-2B5-M	FXCS-5B5-M	3/4"			
FXCS-1B7-M	FXCS-4B7-M	1/2"		Black/Black	Specify
FXCS-2B7-M	FXCS-5B7-M	3/4"			

SEAL-XM LED PILOT LIGHT

SEAL-XM LED PILOT LIGHT						
CATALOG NUMBER		HUB SIZE	DIAGRAM	VOLTAGE③	LENS COLOR	LEGEND PLATE MARKING
BOX & COVER						
DEAD-END	FEED-THRU					
FXCS-1B24CL-M	FXCS-4B24CL-M	1/2"		120V	Clear	Specify
FXCS-2B24CL-M	FXCS-5B24CL-M	3/4"				
FXCS-1B24GL-M	FXCS-4B24GL-M	1/2"		120V	Green	Specify
FXCS-2B24GL-M	FXCS-5B24GL-M	3/4"				
FXCS-1B24RL-M	FXCS-4B24RL-M	1/2"		120V	Red	Specify
FXCS-2B24RL-M	FXCS-5B24RL-M	3/4"				



CONTROLS

SEAL-XM™ SERIES

FACTORY SEALED CONTROL STATIONS

Double LED
Pilot LightPush Button
LED Pilot LightPush/Pull
Mushroom**SEAL-XM DOUBLE LED PILOT LIGHT**

CATALOG NUMBER		HUB SIZE	DIAGRAM	LAMP VOLTS	LENS COLOR	LEGEND PLATE MARKING
BOX & COVER						
DEAD-END	FEED-THRU					
FXCS-1B30CL-M	FXCS-4B30CL-M	1/2"		120V	Clear	Specify
FXCS-2B30CL-M	FXCS-5B30CL-M	3/4"				
FXCS-1B30GL-M	FXCS-4B30GL-M	1/2"		120V	Green	Specify
FXCS-2B30GL-M	FXCS-5B30GL-M	3/4"				
FXCS-1B30RL-M	FXCS-4B30RL-M	1/2"		120V	Red	Specify
FXCS-2B30RL-M	FXCS-5B30RL-M	3/4"				
FXCS-1B30RL-GL-M	FXCS-4B30RL-GL-M	1/2"		120V	Red/Green	Specify
FXCS-2B30RL-GL-M	FXCS-5B30RL-GL-M	3/4"				

SEAL-XM MOMENTARY CONTACT PUSH BUTTON AND LED PILOT LIGHT

CATALOG NUMBER		HUB SIZE	DIAGRAM	LAMP VOLTS	BUTTON COLOR	LENS COLOR	LEGEND PLATE MARKING	
BOX & COVER							BUTTON	LENS
DEAD-END	FEED-THRU							
FXCS-1B13-C-M	FXCS-4B13-C-M	1/2"		120V	Red	Clear	Stop	Specify
FXCS-2B13-C-M	FXCS-5B13-C-M	3/4"						
FXCS-1B13-O-M	FXCS-4B13-O-M	1/2"		120V	Green	Green	Start	Specify
FXCS-2B13-O-M	FXCS-5B13-O-M	3/4"						
FXCS-1B13-U-M	FXCS-4B13-U-M	1/2"		120V	Black	Red	Specify	Specify
FXCS-2B13-U-M	FXCS-5B13-U-M	3/4"						

SEAL-XM MAINTAINED CONTACT PUSH/PULL MUSHROOM

CATALOG NUMBER		HUB SIZE	DIAGRAM	BUTTON COLOR	LEGEND PLATE MARKING
BOX & COVER					
DEAD-END	FEED-THRU				
FXCS-1MMG3-M	FXCS-4MMG3-M	1/2"		Green	Start
FXCS-2MMG3-M	FXCS-5MMG3-M	3/4"			
FXCS-1MMR3-M	FXCS-4MMR3-M	1/2"		Red	Stop
FXCS-2MMR3-M	FXCS-5MMR3-M	3/4"			
FXCS-1MMK3-M	FXCS-4MMK3-M	1/2"		Black	Specify
FXCS-2MMK3-M	FXCS-5MMK3-M	3/4"			



FACTORY SEALED CONTROL STATIONS



Two Position Selector Switch



Three Position Selector Switch

SEAL-XM TWO POSITION SELECTOR SWITCH - MAINTAINED CONTACT

CATALOG NUMBER BOX & COVER		HUB SIZE	LEFT POSITION	RIGHT POSITION	STANDARD NAMEPLATE MARKINGS
DEAD-END	FEED-THRU				
FXCS-1S2A1-M	FXCS-4S2A1-M	1/2"			BLANK & OFF-ON
FXCS-2S2A1-M	FXCS-5S2A1-M	3/4"			
FXCS-1S2A5-M	FXCS-4S2A5-M	1/2"			
FXCS-2S2A5-M	FXCS-5S2A5-M	3/4"			

SEAL-XM THREE POSITION SELECTOR SWITCH - MAINTAINED CONTACT

CATALOG NUMBER BOX & COVER		HUB SIZE	LEFT POSITION	CENTER POSITION	RIGHT POSITION	STANDARD NAMEPLATE MARKINGS
DEAD-END	FEED-THRU					
FXCS-1S3C4-M	FXCS-4S3C4-M	1/2"				BLANK or HAND-OFF-AUTO
FXCS-2S3C4-M	FXCS-5S3C4-M	3/4"				
FXCS-1S3C5-M	FXCS-4S3C5-M	1/2"				
FXCS-2S3C5-M	FXCS-5S3C5-M	3/4"				

SEAL-XM TWO POSITION SELECTOR SWITCH - SPRING RETURN

CATALOG NUMBER BOX & COVER		HUB SIZE	LEFT POSITION	RIGHT POSITION	STANDARD NAMEPLATE MARKINGS
DEAD-END	FEED-THRU				
FXCS-1S2L3F-M	FXCS-4S2L3F-M	1/2"			BLANK & OFF-ON
FXCS-2S2L3F-M	FXCS-5S2L3F-M	3/4"			

SELECTOR SWITCH OPERATION - SPRING RETURN TO LEFT FROM RIGHT - MAINTAINED IN LEFT.

SEAL-XM THREE POSITION SELECTOR SWITCH - SPRING RETURN

CATALOG NUMBER BOX & COVER		HUB SIZE	LEFT POSITION	CENTER POSITION	RIGHT POSITION	STANDARD NAMEPLATE MARKINGS
DEAD-END	FEED-THRU					
FXCS-1S3M6G-M	FXCS-4S3M6G-M	1/2"				BLANK or HAND-OFF-AUTO
FXCS-2S3M6G-M	FXCS-5S3M6G-M	3/4"				

SPRING RETURN TO CENTER FROM LEFT AND RIGHT - MAINTAINED CENTER

FXCS-1S3L6G-M	FXCS-4S3L6G-M	1/2"				BLANK or HAND-OFF-AUTO
FXCS-2S3L6G-M	FXCS-5S3L6G-M	3/4"				

SPRING RETURN TO CENTER FROM RIGHT - MAINTAINED CENTER AND LEFT

FXCS-1S3R6G-M	FXCS-4S3R6G-M	1/2"				BLANK or HAND-OFF-AUTO
FXCS-2S3R6G-M	FXCS-5S3R6G-M	3/4"				

SPRING RETURN TO CENTER FROM LEFT - MAINTAINED CENTER AND RIGHT



CONTROLS

SEAL-XM™ SERIES

FACTORY SEALED CONTROL STATIONS



Keyed Selector Switch

SEAL-XM TWO POSITION KEYED SELECTOR SWITCH - MAINTAINED CONTACT

CATALOG NUMBER		HUB SIZE	LEFT POSITION	RIGHT POSITION	STANDARD NAMEPLATE MARKINGS
BOX & COVER					
DEAD-END	FEED-THRU				
FXCS-1K2A1-M	FXCS-4K2A1-M	1/2"			BLANK & OFF-ON
FXCS-2K2A1-M	FXCS-5K2A1-M	3/4"			
FXCS-1K2A5-M	FXCS-4K2A5-M	1/2"			
FXCS-2K2A5-M	FXCS-5K2A5-M	3/4"			

SEAL-XM THREE POSITION KEYED SELECTOR SWITCH - MAINTAINED CONTACT

CATALOG NUMBER		HUB SIZE	LEFT POSITION	CENTER POSITION	RIGHT POSITION	STANDARD NAMEPLATE MARKINGS
BOX & COVER						
DEAD-END	FEED-THRU					
FXCS-1K3C4-M	FXCS-4K3C4-M	1/2"				BLANK or HAND-OFF-AUTO
FXCS-2K3C4-M	FXCS-5K3C4-M	3/4"				
FXCS-1K3C5-M	FXCS-4K3C5-M	1/2"				
FXCS-2K3C5-M	FXCS-5K3C5-M	3/4"				

SEAL-XM TWO POSITION KEYED SELECTOR SWITCH - SPRING RETURN

CATALOG NUMBER BOX & COVER		HUB SIZE	LEFT POSITION	RIGHT POSITION	STANDARD NAMEPLATE MARKINGS
DEAD-END	FEED-THRU				
FXCS-1K2L3F22D-M	FXCS-4K2L3F22D-M	1/2"			BLANK & OFF-ON
FXCS-2K2L3F22D-M	FXCS-5K2L3F22D-M	3/4"			

SELECTOR SWITCH OPERATION - SPRING RETURN TO LEFT FROM RIGHT - MAINTAINED IN LEFT.

SEAL-XM THREE POSITION KEYED SELECTOR SWITCH - SPRING RETURN

CATALOG NUMBER BOX & COVER		HUB SIZE	LEFT POSITION	CENTER POSITION	RIGHT POSITION	STANDARD NAMEPLATE MARKINGS
DEAD-END	FEED-THRU					
FXCS-1K3M6G32D-M	FXCS-4K3M6G32D-M	1/2"				BLANK or HAND-OFF-AUTO
FXCS-2K3M6G32D-M	FXCS-5K3M6G32D-M	3/4"				

SELECTOR SWITCH - OPERATION - SPRING RETURN TO CENTER FROM LEFT AND RIGHT - MAINTAINED IN CENTER

FXCS-1K3L6G32D-M	FXCS-4K3L6G32D-M	1/2"				BLANK or HAND-OFF-AUTO
FXCS-2K3L6G32D-M	FXCS-5K3L6G32D-M	3/4"				

SELECTOR SWITCH - OPERATION - SPRING RETURN TO CENTER FROM RIGHT - MAINTAINED CENTER AND LEFT

FXCS-1K3R6G32D-M	FXCS-4K3R6G32D-M	1/2"				BLANK or HAND-OFF-AUTO
FXCS-2K3R6G32D-M	FXCS-5K3R6G32D-M	3/4"				

SELECTOR SWITCH - OPERATION - SPRING RETURN TO CENTER FROM LEFT - MAINTAINED CENTER AND RIGHT



FACTORY SEALED CONTROL STATIONS



Class I, Div. 1 & 2, Groups C,D
Class I, Zones 1 & 2, Groups IIB, IIA
Class II, Div. 1 & 2, Groups E,F,G
Class III
Type 3

LISTED - File E53360 and/or E12379

Certified - File LR11714

FEATURES-SPECIFICATIONS

Features

- **Factory Sealed** devices eliminate the need for external sealing. The difference is the use of a sealing plate between the arcing device and the junction box. The sealing plate confines ignited gases, vapors, flames, or dust to the arcing device chamber, preventing them from traveling through the conduit system. Factory poured seals around the wiring pigtails insure safe sealing.
- Lower installation cost
- Type 3 weatherproof
- Color coded wiring-more wiring space-easier field installation
- Lockout accessory available; must be factory installed.
- Ground boss for grounding in the splice box
- Cast conduit hubs 1/2", 3/4" and 1" either dead end or feed through standard in both single and two gang assemblies
- Miniature and standard size push buttons. (Miniature 3/4" overall diameter, standard 1 3/8" overall diameter)
- Key operated selector switches are randomly keyed with keys removable in all positions. Keyed alike or key removable in non-standard positions available from factory.

Materials

- Stainless steel captive screws for cover assembly
- Device bodies and covers are cast copper-free aluminum alloy
- Push button, selector switches and pilot light bodies are copper-free aluminum
- Operating shaft in both push buttons and selector switches are stainless steel

Electrical Rating

Push button stations, selector switches
600 VAC max. heavy duty.

Pilot Light Electrical Ratings:
250 VAC max.


CONTACT BLOCK RATINGS – A600				
CURRENT	120 VAC	240 VAC	480 VAC	600 VAC
INRUSH	60	30	15	12
BREAKING	6	3	1.5	1.2
CARRYING	10	10	10	10

DC RATINGS (MAX. AMPS) – P600		
CURRENT	125 VDC	250 VDC
INRUSH	.55	.27
BREAKING	.55	.27
CARRYING	2.55	2.55




CONTROLS FXB SERIES

FACTORY SEALED SPLICE BOXES SEALING METHODS




FXB-2
Dead End

FXB-5
Feed Thru



FXB-8
Double Gang Dead End



FXB-11
Double Gang Feed Thru

Splice Boxes

The FXB Series of splice boxes are designed for use with the FXCS and FXS Series of cover sub-assemblies.

FXB BACK BOX SELECTION AND DIMENSIONS

CATALOG NUMBER	DESCRIPTION	HUB SIZE	EXTERNAL			MOUNTING	
			LENGTH	WIDTH	DEPTH	VERTICAL	HORIZONTAL
FXB-1	Single gang/Dead-end	1/2"	6-13/16"	3-11/16"	1-3/4"	6-3/16"	2-1/4"
FXB-2	Single gang/Dead-end	3/4"	6-13/16"	3-11/16"	1-3/4"	6-3/16"	2-1/4"
FXB-3	Single gang/Dead-end	1"	6-13/16"	3-11/16"	1-3/4"	6-3/16"	2-1/4"
FXB-4	Single gang/Feed-thru	1/2"	6-13/16"	3-11/16"	1-3/4"	6-3/16"	2-1/4"
FXB-5	Single gang/Feed-thru	3/4"	6-13/16"	3-11/16"	1-3/4"	6-3/16"	2-1/4"
FXB-6	Single gang/Feed-thru	1"	6-13/16"	3-11/16"	1-3/4"	6-3/16"	2-1/4"
FXB-7	Double gang/Dead-end	1/2"	6-13/16"	7-17/32"	2	6-3/16"	2-1/4"
FXB-8	Double gang/Dead-end	3/4"	6-13/16"	7-17/32"	2	6-3/16"	2-1/4"
FXB-9	Double gang/Dead-end	1"	7	7-17/32"	2	6-3/16"	2-1/4"
FXB-10	Double gang/Feed-thru	1/2"	6-13/16"	7-17/32"	2	6-3/16"	2-1/4"
FXB-11	Double gang/Feed-thru	3/4"	6-13/16"	7-17/32"	2	6-3/16"	2-1/4"
FXB-12	Double gang/Feed-thru	1"	7	7-17/32"	2	6-3/16"	2-1/4"

FXB BLANK COVER

CATALOG NUMBER	DESCRIPTION
FX-10	BLANK COVER FOR FXB




Certified File No. LR11714



US LISTED File Number E53360

FXB SPACER

CATALOG NUMBER	DESCRIPTION
FXB075SPCR	SPACER, 3/4" ADDITIONAL DEPTH
FXB10SPCR	SPACER, 1" ADDITIONAL DEPTH
FXB15SPCR	SPACER, 1 1/2" ADDITIONAL DEPTH
FXB20SPCR	SPACER, 2" ADDITIONAL DEPTH



C53



CONTROLS

FXCS SERIES

FACTORY SEALED CONTROL STATIONS



2 Gang Box and
Two Cover Assemblies

FXCS MOMENTARY CONTACT SINGLE PUSH BUTTON

CATALOG NUMBER			HUB SIZE	DIAGRAM	BUTTON COLOR	NAMEPLATE MARKING
COVER WITH DEVICE	COMPLETE UNITS (BOX & COVER)					
	DEAD-END	FEED-THRU				
FXCS-0B1	FXCS-1B1	FXCS-4B1	1/2"		Green	Start
	FXCS-2B1	FXCS-5B1	3/4"			
FXCS-0B2	FXCS-1B2	FXCS-4B2	1/2"		Red	Stop
	FXCS-2B2	FXCS-5B2	3/4"			
FXCS-0B3	FXCS-1B3	FXCS-4B3	1/2"		Black	Specify
	FXCS-2B3	FXCS-5B3	3/4"			

FXCS MOMENTARY CONTACT DOUBLE PUSH BUTTON

CATALOG NUMBER			HUB SIZE	DIAGRAM	BUTTON COLOR	NAMEPLATE MARKING
COVER WITH DEVICE	COMPLETE UNITS (BOX & COVER)					
	DEAD-END	FEED-THRU				
FXCS-0B4	FXCS-1B4	FXCS-4B4	1/2"		Green/Red	Start/Stop
	FXCS-2B4	FXCS-5B4	3/4"			
FXCS-0B4U	FXCS-1B4-U	FXCS-4B4-U	1/2"		Green/Red	Start/Stop
	FXCS-2B4-U	FXCS-5B4-U	3/4"			
FXCS-0B5	FXCS-1B5	FXCS-4B5	1/2"		Green/Green	Specify
	FXCS-2B5	FXCS-5B5	3/4"			
FXCS-0B7	FXCS-1B7	FXCS-4B7	1/2"		Black/Black	Specify
	FXCS-2B7	FXCS-5B7	3/4"			

FXCS PILOT LIGHT

CATALOG NUMBER			HUB SIZE	DIAGRAM	VOLT	LENS COLOR	NAMEPLATE MARKING
COVER WITH DEVICE	COMPLETE UNITS (BOX & COVER)						
	DEAD-END	FEED-THRU					
FXCS-0B24CL	FXCS-1B24-CL	FXCS-4B24-CL	1/2"		120V	Clear	Specify
	FXCS-2B24-CL	FXCS-5B24-CL	3/4"				
FXCS-0B24GL	FXCS-1B24-GL	FXCS-4B24-GL	1/2"		120V	Green	Specify
	FXCS-2B24-GL	FXCS-5B24-GL	3/4"				
FXCS-0B24RL	FXCS-1B24-RL	FXCS-4B24-RL	1/2"		120V	Red	Specify
	FXCS-2B24-RL	FXCS-5B24-RL	3/4"				



FACTORY SEALED CONTROL STATIONS



Pilot Light and 2 Mini P.B.
(Box and Cover)



Double Pilot Lights
(Box and Cover)



Maintained Push Button
(Box and Cover)

FXCS DOUBLE PILOT LIGHTS

FXCS DOUBLE PILOT LIGHTS							
CATALOG NUMBER			HUB SIZE	DIAGRAM	LAMP VOLTS	LENS COLOR	NAMEPLATE MARKING
COVER WITH DEVICE	COMPLETE UNITS (BOX & COVER)						
	DEAD-END	FEED-THRU					
FXCS-0B30CL	FXCS-1B30-CL	FXCS-4B30-CL	1/2"		120V	Clear	Specify
	FXCS-2B30-CL	FXCS-5B30-CL	3/4"				
FXCS-0B30GL	FXCS-1B30-GL	FXCS-4B30-GL	1/2"		120V	Green	Specify
	FXCS-2B30-GL	FXCS-5B30-GL	3/4"				
FXCS-0B30RL	FXCS-1B30-RL	FXCS-4B30-RL	1/2"		120V	Red	Specify
	FXCS-2B30-RL	FXCS-5B30-RL	3/4"				
FXCS-0B30RL-GL	FXCS-1B30RL-GL	FXCS-4B30RL-GL	1/2"		120V	Red/Green	Specify
	FXCS-2B30RL-GL	FXCS-5B30RL-GL	3/4"				

FXCS MOMENTARY CONTACT PUSH BUTTON AND PILOT LIGHT

FXCS MOMENTARY CONTACT PUSH BUTTON AND PILOT LIGHT									
COVER WITH DEVICE	CATALOG NUMBER		HUB SIZE	DIAGRAM	LAMP VOLTS	BUTTON COLOR	LENS COLOR	NAMEPLATE MARKING	
	COMPLETE UNITS (BOX & COVER)							BUTTON	LENS
	DEAD-END	FEED-THRU							
FXCS-0B13-C	FXCS-1B13-C	FXCS-4B13-C	1/2"		120V	Red	Clear	Stop	Specify
	FXCS-2B13-C	FXCS-5B13-C	3/4"						
FXCS-0B13-O	FXCS-1B13-O	FXCS-4B13-O	1/2"		120V	Green	Green	Start	Specify
	FXCS-2B13-O	FXCS-5B13-O	3/4"						
FXCS-0B13-U	FXCS-1B13-U	FXCS-4B13-U	1/2"		120V	Black	Red	Specify	Specify
	FXCS-2B13-U	FXCS-5B13-U	3/4"						

FXCS MOMENTARY CONTACT 2 MINI PUSH BUTTON AND 1 PILOT LIGHT

FXCS MOMENTARY CONTACT 2 MINI PUSH BUTTON AND 1 PILOT LIGHT								
CATALOG NUMBER			HUB SIZE	DIAGRAM	BUTTON COLOR	LENS COLOR	NAMEPLATE MARKING	
COVER WITH DEVICE	COMPLETE UNITS (BOX & COVER)						BUTTON	LENS
	DEAD-END	FEED-THRU						
FXCS-0A15	FXCS-1A15	FXCS-4A15	1/2"	 120 VAC	Red/Green	Red	Stop Start	Specify
	FXCS-2A15	FXCS-5A15	3/4"					

FXCS MAINTAINED CONTACT - PUSH/PULL MUSHROOM

COVER ASSEMBLY CAT. #	CATALOG # WITH LOCKOUT #	CONTACT TYPE	BUTTON COLOR	NAMEPLATE MARKING
FXCS-OMMG3	FXCS-OMMR3-LOM	1NO/1NC	GREEN	Three nameplates supplied (START, STOP, and EMERG STOP).
FXCS-OMMR3		1NO/1NC	RED	
FXCS-OMMK3		1NO/1NC	BLACK	



CONTROLS

FXCS SERIES

FACTORY SEALED CONTROL STATIONS



Selector Switch
(Box and Cover)



Keyed Selector Switch
(Box and Cover)

FXCS TWO POSITION SELECTOR SWITCH – MAINTAINED CONTACT

CATALOG NUMBER							LEFT POSITION		RIGHT POSITION		STANDARD NAMEPLATE MARKINGS
STANDARD COVER WITH DEVICE	HUB SIZE	STANDARD COMPLETE UNITS (BOX & COVER)		KEYED COVER WITH DEVICE	KEYED COMPLETE UNITS② (BOX & COVER)		LEFT CONTACT	RIGHT CONTACT	LEFT CONTACT	RIGHT CONTACT	
		DEAD-END	FEED-THRU		DEAD-END	FEED-THRU					
FXCS-0S2A1	1/2"	FXCS-1S2A1	FXCS-4S2A1	FXCS-0K2A1	FXCS-1K2A1	FXCS-4K2A1					BLANK or OFF-ON
	3/4"	FXCS-2S2A1	FXCS-5S2A1		FXCS-2K2A1	FXCS-5K2A1					
FXCS-0S2A5	1/2"	FXCS-1S2A5	FXCS-4S2A5	FXCS-0K2A5	FXCS-1K2A5	FXCS-4K2A5					
	3/4"	FXCS-2S2A5	FXCS-5S2A5			FXCS-2K2A5	FXCS-5K2A5				

FXCS THREE POSITION SELECTOR SWITCH – MAINTAINED CONTACT

CATALOG NUMBER							LEFT POSITION		CENTER POSITION		RIGHT POSITION		STANDARD NAMEPLATE MARKINGS
STANDARD COVER WITH DEVICE	HUB SIZE	STANDARD COMPLETE UNITS (BOX & COVER)		KEYED COVER WITH DEVICE	KEYED COMPLETE UNITS ^② (BOX & COVER)		LEFT CONTACT	RIGHT CONTACT	LEFT CONTACT	RIGHT CONTACT	LEFT CONTACT	RIGHT CONTACT	
		DEAD-END	FEED-THRU		DEAD-END	FEED-THRU							
FXCS-0S3C4	1/2"	FXCS-1S3C4	FXCS-4S3C4	FXCS-0K3C4	FXCS-1K3C4	FXCS-4K3C4							BLANK or HAND-OFF-AUTO
	3/4"	FXCS-2S3C4	FXCS-5S3C4		FXCS-2K3C4	FXCS-5K3C4							
FXCS-0S3C5	1/2"	FXCS-1S3C5	FXCS-4S3C5	FXCS-0K3C5	FXCS-1K3C5	FXCS-4K3C5							
	3/4"	FXCS-2S3C5	FXCS-5S3C5		FXCS-2K3C5	FXCS-5K3C5							

FXCS TWO POSITION SELECTOR SWITCH – SPRING RETURNED – 1 N.O./1 N.C.

CATALOG NUMBER							LEFT POSITION		RIGHT POSITION		STANDARD NAMEPLATE MARKINGS
STANDARD COVER WITH DEVICE	HUB SIZE	STANDARD COMPLETE UNITS (BOX & COVER)		KEYED COVER WITH DEVICE	KEYED COMPLETE UNITS ^② (BOX & COVER)		LEFT CONTACT	RIGHT CONTACT	LEFT CONTACT	RIGHT CONTACT	
		DEAD-END	FEED-THRU		DEAD-END	FEED-THRU					
FXCS-0S2L3F	1/2"	FXCS-1S2L3F	FXCS-4S2L3F	FXCS-0K2L3F22D	FXCS-1K2L3F22D	FXCS-4K2L3F22D					BLANK or OFF-ON
	3/4"	FXCS-2S2L3F	FXCS-5S2L3F		FXCS-2K2L3F22D	FXCS-5K2L3F22D	TYPE OPERATION – Spring return to left from right – Maintained in left – 1 N.O. Contact – 1 N.C. Contact				

FXCS THREE POSITION SELECTOR SWITCH – SPRING RETURNED – 2 N.O.

CATALOG NUMBER							LEFT POSITION		CENTER POSITION		RIGHT POSITION		STANDARD NAMEPLATE MARKINGS
STANDARD COVER WITH DEVICE	HUB SIZE	STANDARD COMPLETE UNITS (BOX & COVER)		KEYED COVER WITH DEVICE	KEYED COMPLETE UNITS② (BOX & COVER)		LEFT CONTACT	RIGHT CONTACT	LEFT CONTACT	RIGHT CONTACT	LEFT CONTACT	RIGHT CONTACT	
		DEAD-END	FEED-THRU		DEAD-END	FEED-THRU							
FXCS-0S3M6G	1/2"	FXCS-1S3M6G	FXCS-4S3M6G	FXCS-0K3M6G32D	FXCS-1K3M6G32D	FXCS-4K3M6G32D							BLANK or HAND-OFF-AUTO
	3/4"	FXCS-2S3M6G	FXCS-5S3M6G		FXCS-2K3M6G32D	FXCS-5K3M6G32D	TYPE OPERATION — Spring return to center from left or right — Maintained in center — 2 N.O. Contacts						
FXCS-0S3L6G	1/2"	FXCS-1S3L6G	FXCS-4S3L6G	FXCS-0K3L6G32D	FXCS-1K3L6G32D	FXCS-4K3L6G32D							
	3/4"	FXCS-2S3L6G	FXCS-5S3L6G		FXCS-2K3L6G32D	FXCS-5K3L6G32D	TYPE OPERATION — Spring return to center from right — Maintained center and left 2 N.O. Contacts						
FXCS-0S3R6G	1/2"	FXCS-1S3R6G	FXCS-4S3R6G	FXCS-0K3R6G32D	FXCS-1K3R6G32D	FXCS-4K3R6G32D							
	3/4"	FXCS-2S3R6G	FXCS-5S3R6G		FXCS-2K3R6G32D	FXCS-5K3R6G32D	TYPE OPERATION — Spring return to center from left — Maintained center and right 2 N.O. Contacts						